


4x3 matrix keypad

Produktkode: 278aa

Tilgjengelighet: 3

Pris: kr. 20,00



Kort beskrivelse

Matrix Array 12 Key Membrane Switch Keypad Keyboard For Arduino AVR 4 x 3 CC

Beskrivelse

Features:

Contact resistance of 500 (Ω)

Insulation resistance 100M (Ω)

Key Operating Force 150-200N

Rebound time 1 (ms)

Life of 100 million (times)

Operating Temperature 60 degree

The electronic characteristics

Circuit Rating: 35V (DC), 100mA, 1W

Contact resistance: 10Ω ~ 500Ω (Varies according to the lead lengths and different from those of the material used)

Insulation resistance: 100MΩ 100V

Dielectric Strength: 250VRms (50 ~ 60Hz 1min)

<http://playground.arduino.cc/Main/KeypadTutorial>

[Bibliotek](#)

Skisse 1

#include

```
const byte ROWS = 4; //four rows
const byte COLS = 3; //three columns
char keys[ROWS][COLS] = {
  {'1','2','3'},
  {'4','5','6'},
  {'7','8','9'},
  {'#','0','*'}
};
byte rowPins[ROWS] = {5, 4, 3, 2}; //connect to the row pinouts of the keypad
byte colPins[COLS] = {8, 7, 6}; //connect to the column pinouts of the keypad

Keypad keypad = Keypad( makeKeymap(keys), rowPins, colPins, ROWS, COLS );

void setup(){
  Serial.begin(9600);
}

void loop(){
  char key = keypad.getKey();

  if (key != NO_KEY){
    Serial.println(key);
  }
}
```

Skisse 2

```
/*
|| Written by Dougie Kinnear November 2012
|| building on Nathan Sobieck's|| Simple Password Entry Using Matrix Keypad
|| 4/5/2012 Updates Nathan Sobieck: Nathan@Sobisource.com|| I used a Textstar LCD
for visul output. The code may need changed
|| for other LCD's. Control codes may also appear in the
|| serial monitor. See the Textstar data sheet for control codes|| This sketch is discussed on
my blog
|| http://www.digitalmaker.co.uk/86/ ?
|| look under the tags PIN, Textstar, Keypad
|| Please get in touch with any comments, suggestions etc.|| Many thanks to Nathan for
sharing his work
```

*/

// # is to validate password//////////////////////////////////////include

//http://www.arduino.cc/playground/uploads/Code/Password.zip

#include //http://www.arduino.cc/playground/uploads/Code/Keypad.zipint greenled(11);

int redled(12);//----- Keypad set up/mapping -----Password password

Password("1234"); // Set the password hereconst byte ROWS = 4; // Four rows

const byte COLS = 3; // columns

char keys[ROWS][COLS] = {

{ '1?', '2?', '3' },

{ '4?', '5?', '6' },

{ '7?', '8?', '9' },

{ '*', '0?', '#' }

};byte rowPins[ROWS] = { 8,7,6,5}; // Assign board pins to keypad rows

byte colPins[COLS] = { 4,3,2}; // Assign board pins to keypad columnsKeypad keypad =

Keypad(makeKeymap(keys), rowPins, colPins, ROWS, COLS);

//-----void setup(){

{

pinMode(11, OUTPUT); //green light

pinMode(12, OUTPUT); //red light

Serial.begin(9600);

}

keypad.addEventListener(keypadEvent); //add an event listener for this

keypaddelay(100); // A further delay to allow the LCD to initialiseSerial.write(254); //

Tell LCD multiple command characters are coming

Serial.write(67); // Send a 'C' = Cursor set up command

Serial.write(4); // Set cursor to flashing underlinedigitalWrite(12, HIGH); // red LED on

delay(2000); // The LCD should be ready now – these delays can be

alteredSerial.write(12); // This is a command to clear the screen and set the cursor to Line
1 column 1

Serial.println("Enter a PIN then"); // Print the text to the screen

Serial.println("press '#'"); // Print the text to the screen}void loop(){

keypad.getKey();

} void keypadEvent(KeypadEvent eKey){ // This is what happens during a keypad

eventswitch (keypad.getState()){

case PRESSED:

Serial.print(eKey); // When a key is pressed * is printedswitch (eKey){

case '#': checkPassword(); break; // press # to check entry

default: password.append(eKey);

}

```

}
}void checkPassword(){

if (password.evaluate()){ // If it's correct do this

Serial.write(12);
Serial.println("CORRECT");
digitalWrite(12, LOW);
digitalWrite(11, HIGH);

delay(3000);

digitalWrite(11, LOW);
digitalWrite(12, HIGH);
password.reset(); // reset for next event

Serial.println("Enter a PIN then"); // Print the text to the screen
Serial.println("press '#"); // Print the text to the screen

}

else{

Serial.write(12); // If it's wrong do this

Serial.println("INCORRECT");
Serial.println("TRY AGAIN");

delay(50); // flash the red LED
digitalWrite(12,LOW);
delay(50);
digitalWrite(12, HIGH);
delay(50);
digitalWrite(12,LOW);
delay(50);
digitalWrite(12, HIGH);
delay(50);
digitalWrite(12,LOW);
delay(50);
digitalWrite(12, HIGH);
delay(50);
digitalWrite(12,LOW);
}
}
}

```

```
delay(50);
digitalWrite(12, HIGH);
delay(50);
digitalWrite(12,LOW);
delay(50);
digitalWrite(12, HIGH);
delay(50);
digitalWrite(12,LOW);
delay(50);
digitalWrite(12, HIGH);
delay(50);
digitalWrite(12,LOW);
delay(50);
digitalWrite(12, HIGH);
delay(50);
digitalWrite(12,LOW);
delay(50);
digitalWrite(12, HIGH);
delay(50);
digitalWrite(12,LOW);
delay(50);
digitalWrite(12, HIGH);
delay(50);
digitalWrite(12,LOW);
delay(50);
digitalWrite(12, HIGH);
delay(50);
digitalWrite(12,LOW);
delay(50); // stop flashing the red LED

digitalWrite(12, HIGH);
password.reset(); // reset for next event

delay(2500);
```

```
Serial.println("Enter a PIN then"); // Print the text to the screen
Serial.println("press '#'"); // Print the text to the screen
}
```

Produktgalleri

